

ELECTRICAL LABORATORY- TEST REPORT
Safety of Machinery –Electrical Equipment of The Machines
Part 1: General Requirements

Test Report N°.....
Date of issue..... 04-06-2015
Sample date in..... 11-05-2015
Date of performance..... 11-05-2015 to 11-05-2015
Applicant.....
Customer.....

Sample description..... Control Panel For Tablet Press
Sample Condition..... Ok
Customer reference..... N/A


Trade mark / Manufacturer..
Model / Type / Reference.... Lumina Press 20-D (L101/102)
Ratings..... 415 V ± 10% AC, 3 Phase, 50 Hz ± 2%, 15A
Test method(s)..... BS EN 60204-1:2009

Overall verdict Pass
 Fail

Page 1 of 35

REMARKS: This report is governed by, and incorporates by reference, the Condition of testing as posted at its date of issuance and is intended for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. **This report sets forth solely our findings with respect to the test samples identified herein.** It includes all of the test requested by you and the results thereof based upon the information that you provided us with. You have 10 calendar days from the date of issuance of this report to notify us of any material error or omission; provided, however, that such notice shall be written and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Tests are destructive and non reversible, the submitted samples will not return to their original conditions. The client acknowledges that any remaining part of the sample will be discarded if not retrieved in a period of 30 calendar days from the date of issuance of this report.




INSTITUTE OF TESTING AND CERTIFICATION (INDIA) PVT. LTD.

BS EN 60204-1			
Clauses	Requirement – Test	Results – Remarks	Verdict
5.	INCOMING SUPPLY CONDUCTOR TERMINATIONS AND DEVICES FOR DISCONNECTING AND SWITCHING OFF		
5.1	Incoming supply conductor terminations		
	The electrical equipment of the machine shall have only one incoming supply connection	Single Incoming Supply	P
	Unless a plug is supplied it is recommended that the supply conductors are terminated at the supply disconnecting devices		N/A
	Neutral conductor “N” should be indicated in the technical documentation and label “N” is provided at neutral conductor	Neutral conductor identified as ‘N’	P
	There shall be no connection between neutral conductor and protective bonding circuit or combined PEN-terminals.	The neutral & protective bonding circuit has separate wires	P
	All terminals of incoming supply shall be clearly marked	(Clear indication for supply voltage provided)	P
5.2	Terminal for connection to external protective Earthing system		
	Terminal for connection of external protective conductor provided and marked with “PE” or with graphical symbol  by use of bicolor combination GREEN/YELLOW	Provided	P
	Cross section of incoming PE conductor shall be according to table 1	In Compliance	P
5.3	Supply disconnecting device		
5.3.1	A supply disconnecting device shall be provided for each incoming supply to the machine.	Rotary switch provided for incoming supply	P
5.3.2	The supply disconnecting device shall be one of the following:		
	a) A switch-disconnector with or without fuses		N/A
	b) A disconnector with or without fuses, which has an auxiliary contact that in all cases causes switching device to break the load circuit.		N/A
	c) circuit breaker suitable for isolation		N/A
	d) any other switching device in accordance with an IEC product standard for that device and which meets the isolation requirements of IEC 60947-1 as well as a utilization category		P
	e) Plug/socket combination for flexible cable supply		N/A
BS EN 60204-1			
Clauses	Requirement – Test	Results – Remarks	Verdict

INSTITUTE OF TESTING AND CERTIFICATION (INDIA) PVT. LTD.

5.3.3	When supply disconnecting device is one of type from 5.3.2 a) to d) it shall fulfill all of the following requirements		
	Isolates the electrical equipment from the supply and have one OFF and one ON position only & 'O' & 'I' marked		P
	Switch shall have external operating means e.g. handle.		P
	Colour black or gray preferred		N/A
	Position indication which cannot indicates the OFF-position until all contacts are actually open	In OFF position the main supply is disconnected	P
	Locking means provided to lock in OFF-Position		N/A
	For Plug/Socket type		
	Have the sufficient switching capability		N/A
5.3.4	Operating means		
	Operating means shall be located between 0.6m and 1.9m above service level	In compliance	P
5.3.5	Following circuits need not disconnected by supply disconnecting device.		
	Lighting circuits during maintenance or repair		N/A
	Plug/socket-outlets exclusively used for maintenance or repair		N/A
	Under voltage protection circuits used for automatic tripping only at power supply failure		N/A
	Control circuits for interlocking purpose		N/A
	<i>It is recommended that such circuits be provided with their own disconnecting devices</i>		N/A
	Where such a circuit is not disconnected by supply disconnecting device		
	<ul style="list-style-type: none"> Permanent warning label shall be appropriately placed 		N/A
5.4	Disconnecting devices to prevent unexpected start-up		
	Means shall be provided to prevent unexpected start up		P
	Suitable placed	In compliance	P
	Readily identifiable	In compliance	P
	<i>Devices used for isolation function can be used for this purpose such as Disconnectors ,withdraw able fuse links</i>		P
	<i>Devices that do not provide the isolation function may also be used where e.g contactor switch</i>		
	<ul style="list-style-type: none"> There is no hazard from electric shock 		P
	<ul style="list-style-type: none"> The switching off means remains effective throughout the work 		P

INSTITUTE OF TESTING AND CERTIFICATION (INDIA) PVT. LTD.

BS EN 60204-1			
Clauses	Requirement – Test	Results – Remarks	Verdict
	<ul style="list-style-type: none"> Ground bond test with 10A and 24V and resistance should be less than 0.1Ω 	 <p>Measured Resistance is 46.7 mΩ</p>	P
18.3	Insulation Resistance test		
	Insulation resistance measured with 500V DC between power circuit conductors and PE circuit is to be 1 MΩ. Test made on individual sections of complete electrical installation	 <p>Measured resistance value is >9900 MΩ</p>	P
18.4	Voltage test		
	Electrical equipment should withstand a test voltage applied twice the rated equipment or 1000V whichever is higher for 1 sec.	 <p>No voltage break down and no flashover occur</p>	P
18.5	Protection against residual voltage		
	Tests for protection against residual voltages are performed to ensure compliance with Cl. 6.2.4		N/A
18.6	Functional tests		
	The functions of electrical equipment shall be tested		P

INSTITUTE OF TESTING AND CERTIFICATION (INDIA) PVT. LTD.

BS EN 60204-1			
Clauses	Requirement – Test	Results – Remarks	Verdict

Test Results:

Sr. No	TEST CONDUCTED	TEST CONDITIONS	TEST REQUIREMENTS	RESULTS
01	HIGH VOLTAGE TEST	Test voltage: 1KV/50 Hz Test Duration: 1second Test Part: Between conductors of all circuits & protective bonding circuit.	Shall withstand without breakdown	P
02	INSULATION RESISTANCE TEST	Test Voltage: 500V D.C Test part: Between power circuit conductors & protective bonding	Shall not be Less than 1 MOhm	P (Rmeas → >>9900 MΩ)
03	EARTH CONTACT RESISTANCE TEST	Test Current: 10A/24V Test Part: Between protective earth terminals and body that is part of the protective bonding circuit.	Calculated Earth Contact Resistance from current & drop in voltage shall not exceed 0.1 ohm	P (Rmeas → 64.4 mΩ)
		Test Current: 10A/24V Test Part: Between protective earth terminals and door that is part of the protective bonding circuit.		P (Rmeas → 46.7 mΩ)

REMARKS:

1. All the tests conducted as per the standard specification.
2. The test results pertain to the sample submitted for testing.
3. Abbreviations used:
Info - Information, Mfr. – Manufacturer, NM – Not Mentioned, IP- Ingress Protection, Cl. – Clause, Temp. – Temperature, Ckt. – Circuit, amb. – Ambient, Sr. No. – Serial number, N/A-Not applicable, P-Pass